


1. FRONT PANEL CMB 101 BLACK LINE




- | | |
|--|---------------------------------------|
| 1. UNBALANCED 1/4" JACK INPUT | 7. MID LOW EQUALIZATION CONTROL KNOB |
| 2. SCOOPED SWITCH
中音域をカットして低音域と高音域をブーストします。
スラップサウンドに適したトーン。 | 8. MID HIGH EQUALIZATION CONTROL KNOB |
| 3. GAIN | 9. HIGH EQUALIZATION CONTROL KNOB |
| 4. BOOST SWITCH | 10. MASTER VOLUME LEVEL KNOB |
| 5. BOOST LED | 11. AUX IN |
| 6. LOW EQUALIZATION CONTROL KNOB | 12. PHONES OUTPUT |
| | 13. ON LED |
| | 14. MAIN ON/OFF SWITCH |

2. REAR PANEL CMB 101 BLACK LINE




- | |
|-------------------------|
| 1. AC POWER SOCKET |
| 2. PRE OUT (unbalanced) |

3. FRONT PANEL CMB 121 BLACK LINE / CMB 151 BLACK LINE



- | | |
|--|---------------------------------------|
| 1. UNBALANCED 1/4" JACK INPUT | 7. MID LOW EQUALIZATION CONTROL KNOB |
| 2. SCOOPED SWITCH
中音域をカットして低音域と高音域をブーストします。
スラップサウンドに適したトーン。 | 8. MID HIGH EQUALIZATION CONTROL KNOB |
| 3. GAIN | 9. HIGH EQUALIZATION CONTROL KNOB |
| 4. BOOST SWITCH | 10. MASTER VOLUME LEVEL KNOB |
| 5. BOOST LED | 11. AUX IN |
| 6. LOW EQUALIZATION CONTROL KNOB | 12. PHONES OUTPUT |
| | 13. ON LED |

3. REAR PANEL CMB 121 BLACK LINE / CMB 151 BLACK LINE



- | |
|----------------------------|
| 1. MAIN ON/OFF SWITCH |
| 2. AC POWER SOCKET |
| 3. SEND EFFECT 1/4" JACK |
| 4. RETURN EFFECT 1/4" JACK |
| 5. GROUND LIFT SWITCH |
| 6. XLR LINE OUT (balanced) |

5. TECHNICAL DETAILS

CMB 101 Black Line

Speaker: 1x10"
EQ: 4-band
Controls: GAIN | MASTER VOLUME | SCOOPED and BOOST switches
Others: AUX IN | PHONES OUT | PREAMP OUT
Output Power: 40W
Dimensions: 37.5cm (w), 36.5 cm (h), 27 cm (d)
Weight: 9.7 kg

CMB 121 Black Line

Speaker: 1x12"
EQ: 4-band
Controls: GAIN | MASTER VOLUME | SCOOPED and BOOST switches
Others: AUX IN | PHONES OUT | XLR LINE OUT
Output Power: 150W
Dimensions: 44cm (w), 44 cm (h), 36.2 cm (d)
Weight: 16.5 kg

CMB 151 Black Line

Speaker: 1x15"
EQ: 4-band
Controls: GAIN | MASTER VOLUME | SCOOPED and BOOST switches
Others: AUX IN | PHONES OUT | XLR LINE OUT
Output Power: 150W
Dimensions: 44 cm (w), 55 cm (h), 36 cm (d)
Weight: 19 kg

POWER REQUIREMENT 70W: CMB 101 BLACK LINE
150W: CMB 121 BLACK LINE / CMB 151 BLACK LINE
100V: 50/60Hz

注意：工場出荷時に使用される国のボルテージに設定されています。改造によるボルテージの変更はおやめください。

警告

CMB Black Line コンボは、販売された国でできるように製造されており、工場出荷時にその国の電圧にプリセットされています。したがって、アンプを AC 電源に接続する前に、アンプに正しい電圧を送信していることを確認してください。認証の問題により、電圧は変更できない場合があります。